

DSP1016B0



Product

Display with 4 Rows of 4 1" Digits

Description:

Quad Display with 4 Rows of 4 Digits, 1" High Red Solid-Segment Digits.

Item: DSP1016B0

UPC: 788581650424

EAN: 0788581650424

Stock Status: Usually in stock.

Dimensions: 10" x 8" x 2.5"

Weight: 4 lbs.

MSRP: \$595.00

Specifications

- (1) Two RJ45 modular connectors for RS422 serial data transmission and reception.
- (1) Two RJ11 modular connectors for accessories.
- (1) RJ11 modular connector for remote Start, Stop and Reset inputs.
- (1) Power requirements: 10-18 VAC or 12-24 VDC power.
- (1) Current consumption: 500MA maximum per digit.
- (1) Construction: Metal enclosure with transparent red acrylic front.

Mounting methods

- (1) Standard mounting is 2 key hole slots spaced 9 inches apart for wall mounting.

- (1) There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.
- (1) There is one 1/4-20 nut on the bottom of the unit for attaching camera style tripod.

Features

- (1) Quad Seven segment Display with 1" high LED digits.
- (1) This Display may be wall-mounted, hung from hooks.
- (1) This unit can display production data, tally count, scores or any other numeric data. It can also display limited alphabetic characters.

Features with optional equipment

- (1) Production Monitoring.
- (1) Count Up Timer.
- (1) Count Down Timer. (0 to 99.59 MM:SS or 0 to 99:59:59 HH:MM:SS).
- (1) User-programmable stored settings.
- (1) Built-in time-of-day clock displays hours/minutes in 12/24 hour time or minutes/seconds.
- (1) Button to turn beeper on/off.

Item Includes

- (1) DSP1016B0 Quad LED display
- (1) RC Reference card
- (1) WD Wiring diagram
- (1) M8BK025F Cable, 25ft, Cat-5
- (1) Not Included: Transformer, Keypad or Controller.

Required Accessories

- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer

Stand alone, choose any Alzatex TimeKeeper™.

Examples:

- (1) DC117B6-PROD1 Production Monitor TAKT time Controller with SD card memory.
- (1) TMR221B9-PROD1 Production Monitor TAKT time Controller.

When using a PLC or PC, use the RS232 adapter

- (1) PS1DB9B RS232 to RJ11 jack converter

Optional Accessories

- (1) DSP254B Large LED wall display
- (1) RYG11ABBK Red-yellow-green indicator lamps