

RLY15B-GC



Product

Ground Closure Module 5 GC Outputs

Description:

Flush-mount five channel module with ground closure outputs to operate up to five devices or to control Red-Yellow-Green, beeper and run status with programmable beep tones, and connector for external speaker (black metal). Fits into double gang electrical box.

Item: RLY15B-GC

UPC: 788581651209

EAN: 0788581651209

Stock Status: Usually in stock.

Dimensions: 4.5" x 4.5" x 1.5"

Weight: 1 lbs.

MSRP: \$299.00

Specifications

- RJ11, RJ45 and Power connectors.
- Audio output (2 watt) for a speaker, that will generate user-programmable audible tones.
- Four ground closure inputs to connect remote buttons and/or sensors.
- Ground closure 200mA output for optional beeper. (not included).
- Ground closure 200mA outputs for Green, yellow, red status and running status.

- Ground closure outputs can drive resistive or inductive loads.
- Construction: Metal flush mount plate, black powder coated finish.
- Power requirements: 10-13VAC or 12-15VDC.
- Current consumption: 50mA to 950mA depending on load.

Features

- Works with The TimeKeeper™, Alzatex, Inc.'s zero to 99.59 minute Count Up/Down Timers.
- Remotely control any device from a PLC, Crestron, AMX or computer.
- Multiple devices may be daisy chained in a single system.
- Each unit is uniquely addressable with one of 32 addresses.
- Green-Talk; Yellow-Wrap it up; Red-Done LED indicators.
- Built-in beep tone generator with 2 watt audio amplifier output to directly drive 4-16 ohm speakers.
- The Count Up/Down TimeKeeper™ can enable or disable the beeper.
- The volume control permits you to set the volume level for the user-programmable audible tones.
- The unit mounts in a standard double gang electrical box.

In the Box

- RLY15B-GC Relay module
- (4) FHO632-500 Screws, oval head, 6-32x1/2".
- M8BK003F Cable, 3ft, Cat-5
- RC Reference guide
- WD Wiring diagram
- Not Included: Transformer

Required Accessories

- WT12VAC1200MA-RA 12V AC, 1200mA transformer

Optional Accessories

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- TMR223B5-SM Count up/down timer
- TMR223B8-SM Count up/down timer
- TMR223B8-FM Count up/down timer