

# RYG401A



## Product

Red-Yellow-Green signal lights, 4"

### Description:

Large Red-Yellow-Green unit with a single 4" diameter round 72 LED array that changes color. Includes 24-red, 24-yellow, 24-green LEDs in a single cluster.

**Item:** RYG401A

**UPC:** 788581651315

**EAN:** 0788581651315

**Stock Status:** When I have a good enclosure built, I will add this item

**Dimensions:** 6" x 6" x 2.75"

**Weight:** 3 lbs.

**MSRP:** \$475.00

## Specifications

- (1) RJ45 modular connector for RS422 serial data input.
- (1) RJ11 modular connectors for serial data input.
- (1) Ground closure inputs to manually operate the Green, Yellow, Red Indicators and the beeper.
- (1) Power connector (2.1x5.5mm).
- (1) Test button for testing and configuration.
- (1) Screw terminal connector for loud beeper.
- (1) Screw terminal connector for 8 ohm speaker.

- (1) Construction: Metal enclosure, black powder coated finish.
- (1) Power requirements: 10-13VAC or 12-15VDC.
- (1) Current consumption: 450mA.

## Features

- (1) Red-Yellow-Green Audience signal lights.
- (1) Works with The TimeKeeper™, Alzatex, Inc.'s zero to 99.59 minute Count Up/Down Timers.
- (1) May be powered using AC or DC power.
- (1) Low power consumption.
- (1) Optional built-in internal beeper. The Count Up/Down TimeKeeper™ can enable or disable the beeper.
- (1) Green-Talk; Yellow-Wrap it up; Red-Done LED Indicators.
- (1) The Wall Mount or portable Red-Yellow-Green Indicator is available with black or OAK enclosure.
- (1) Audio output (2 watt) for a speaker, that will generate user-programmable audible tones.

## Item Includes

- (1) RYG401A Indicator lamp module
- (1) RC Reference card
- (1) WD Wiring diagram
- (1) M4C007F 7ft 4-conductor standard modular phone cord.
- (1) Not Included: Transformer