

TMR218B11-SM



Product

Clock/Timer, 6 Digits

Description:

Surface-mount Count Up/Down Timer with time-of-day clock and tally button, six-digit LED Display and Red-Yellow-Green LED's with 6 stored presets. (Metal enclosure).

Item: TMR218B11-SM

UPC: 788581650264

EAN: 0788581650264

Stock Status: In stock. Once stock is depleted, will be replaced by TMR216B16_SM.

Dimensions: 6.25" x 5" x 2"

Weight: 1.15 lbs.

MSRP: \$549.00

Specifications

- (1) Two Serial data RJ11 connectors for accessories.
- (1) One RS422 output with RJ45 connector for accessories.
- (1) Ground closure 200mA output for optional beeper. (not included).
- (1) Construction: Metal enclosure, black powder coated finish.
- (1) Power requirements: 10-18 VAC or 12-24 VDC power.
- (1) Current consumption: 100ma.

Features

- (1) Easy to use. Press Reset. Turn knob to set the desired time. Press Start.
- (1) Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.
- (1) Count Up elapsed Timer.
- (1) Count Down time remaining Timer.
- (1) Up to 6 user-programmable stored settings.
- (1) 0-99.59.59 HH:MM:SS.
- (1) User-programmable Green, Yellow and Red warning Indicators.
- (1) The Select button selects between setting hours, minutes and seconds.
- (1) The Mode button selects between Count Up and Count Down modes. You may change between Count Up and Count Down modes while the timer is running. In Count Down mode, the timer stops when it reaches zero. In Count Up mode, the timer keeps running when the preset time is reached.
- (1) Six-digit LED seven-segment Display with 0.56" high digits.
- (1) Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- (1) Six-digit count up timer settable to Hour:Min:Sec.
- (1) Six-digit count down timer settable to Hour:Min:Sec.
- (1) Made of ruggedized aluminum construction.

Item Includes

- (1) TMR218B11-SM Count up/down timer
- (1) RC Reference card
- (1) WD Wiring diagram
- (1) M4C007F 7ft Standard Modular phone cord
- (1) Not Included: Transformer

Required Accessories

- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer

Optional Accessories

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- (1) DSP254B Large LED wall display
- (1) DSP506B Large LED wall display
- (1) DSP704B Large LED wall display
- (1) PS422A2 Displays with 7" or larger digits require a PS422A2 adapter.
- (1) RYG11ABBK Red-yellow-green indicator lamps

If you have a Crestron, AMX, RCI or PC, use the RS232 adapter

- (1) PS1DB9B RS232 to RJ11 jack converter