

# TMR218B6BK-RF2



## Product

UP/DN Timer, 4-DIGIT Display, 2 PRESETS

### Description:

Wireless 2.4GHz Count Up/Down Timer with 4-digit LED Display with Red-Yellow-Green LEDs, and two presets (Black enclosure).

**Item:** TMR218B6BK-RF2

**UPC:** 788581650233

**EAN:** 0788581650233

**Stock Status:** If out of stock, the TMR218B11-SM-RF2 with 6 stored presets will be substituted.

**Dimensions:** 6.75" x 4.75" x 2.5"

**Weight:** 1 lbs.

**MSRP:** \$649.00

## Specifications

- (1) Integrated 2.4GHz wireless transceiver.
- (1) Two Serial data RJ11 connectors for accessories.
- (1) Ground closure 200mA output for optional beeper. (not included).
- (1) Construction: Black ABS enclosure.
- (1) Power requirements: 10-18 VAC or 12-24 VDC power.
- (1) Current consumption: 100ma.

## Features

- (1) Easy to use. Press Reset. Turn knob to set the desired time. Press Start.

- (1) Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.
- (1) Count Up elapsed Timer.
- (1) Count Down time remaining Timer.
- (1) Up to 2 user-programmable stored settings.
- (1) 0-99.59 MM:SS or 0-99:59 HH:MM.
- (1) User-programmable Green, Yellow and Red warning Indicators.
- (1) The Select button selects between setting hours, minutes and seconds.
- (1) The Mode button selects between Count Up and Count Down modes. You may change between Count Up and Count Down modes while the timer is running. In Count Down mode, the timer stops when it reaches zero. In Count Up mode, the timer keeps running when the preset time is reached.
- (1) Four-digit LED seven-segment Display with 0.56" high digits.
- (1) Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- (1) Four-digit count up timer settable to Hour:Min or Min:Sec.
- (1) Four-digit count down timer settable to Hour:Min or Min:Sec.
- (1) Four-digit count up timer settable to Day:Hour, Hour:Min, Min:Sec or Sec.Hundredths.
- (1) Four-digit count down timer settable to Day:Hour, Hour:Min or Min:Sec.
- (1) Made of ruggedized aluminum construction.

## Item Includes

- (1) TMR218B6BK-RF2 Count up/down timer
- (1) RC Reference card
- (1) WD Wiring diagram
- (1) Not Included: Transformer

## Required Accessories

- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer

## Optional Accessories

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- (1) DSP254B Large LED wall display
- (1) DSP506B Large LED wall display
- (1) DSP704B Large LED wall display
- (1) RYG11ABBK Red-yellow-green indicator lamps
- (1) ADD-RF-MX04A RF 2.4GHZ Transceiver, for top of display.