

TMR221B8-DUAL



Product

DUAL UP/DN Timer, CLOCK, 4-DIG Displays

Description:

Dual Surface-mount Count Up/Down Timer with time-of-day clock, 4-digit LED Display and Red-Yellow-Green LED's with remote Start/Stop and remote Start/Reset. Mounted in sloping Oak enclosure.

Item: TMR221B8-DUAL

UPC: 788581650349

EAN: 0788581650349

Stock Status: I intend to replace this with a different product TBD. The current version does not work well. Maybe the TMR216 or the DS592???

Dimensions: 10" x 6.5" x 2.5"

Weight: 2.8 lbs.

MSRP: \$1,295.00

Specifications

- (1) RJ45 modular connector for RS422 serial data output.
- (1) RJ11 modular connector for remote Start, Stop and Reset inputs.
- (1) Ground closure 200mA output for optional beeper. (not included).
- (1) Power requirements: 10-18 VAC or 12-24 VDC power.
- (1) Current consumption: 100ma.
- (1) Construction: Light oak enclosure with a black powder coated steel front.

Features

- (1) Six user-programmable stored settings.
- (1) Dual Count Up Timers.
- (1) Dual Count Down Timers. (0 to 99.59 MM:SS or 0 to 99:59 HH:MM).
- (1) User-programmable Green, Yellow and Red warning Indicators.
- (1) Internal beeper provides audible sound when the timer reaches zero.
- (1) Button to turn beeper on/off.
- (1) Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- (1) Four-digit count up timer settable to Day:Hour, Hour:Min, Min:Sec or Sec.Hundredths.
- (1) Four-digit count down timer settable to Day:Hour, Hour:Min or Min:Sec.
- (1) Built-in time-of-day clock displays hours/minutes in 12/24 hour time or minutes/seconds.

Item Includes

- (1) TMR221B8-DUAL Dual Count up/down timer.
- (1) RC Reference card
- (1) WD Wiring diagram
- (1) M4C007F 7ft Standard Modular phone cord
- (1) Not Included: Transformer

Required Accessories

- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer

Optional Accessories

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- (1) DSP254B Large LED wall display
- (1) DSP506B Large LED wall display
- (1) DSP704B Large LED wall display
- (1) PS422A2 Displays with 7" or larger digits require a PS422A2 adapter.
- (1) RYG11ABBK Red-yellow-green indicator lamps

If you have a Crestron, AMX, RCI or PC, use the RS232 adapter

- (1) PS1DB9B RS232 to RJ11 jack converter