

TMR592B-NEMA4



Product

Dual Up/Dn Timer 2X16 LCD Disp NEMA4X

Description:

Count Up/Down Timer with 8 buttons and a knob, 2x16 LCD Display in a NEMA4X enclosure.

Item: TMR592B-NEMA4

UPC: 788581650363

EAN: 0788581650363

Stock Status: Usually in stock. When ordering, you must specify application details so that we can load the correct software for your application. Allow 2 weeks lead time.

Dimensions: 6" x 6" x 3.5"

Weight: 1.9 lbs.

MSRP: \$595.00

Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- RJ11 modular connector for remote Start, Stop and Reset inputs.
- Power requirements: 10-18 VAC or 12-24 VDC power.
- Display: Backlit LCD Display with 2 lines of 16 characters.
- Current consumption: 160MA max.
- Construction: Nema 4X enclosure with clear acrylic door to access controls.

Features

- Dual Count Up Timers with ground closure inputs or optional Start, Stop and Reset buttons.
- Use Timer 1 to keep track of individual events.
- Use Timer 2 to keep track of total time.
- Integrated time-of-day Clock.
- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Six-digit count up timer settable to Day:Hour:Min, Hour:Min:Sec, or Min:Sec.Hundredths.
- Six-digit count down timer settable to Day:Hour:Min, Hour:Min:Sec.

In the Box

- TMR592B-NEMA4 Dual Count up/down timer.
- RC Reference guide
- WD Wiring diagram
- Not Included: Transformer, cables

Required Accessories

- WT12VAC1200MA-RA 12V AC, 1200mA transformer

Optional Accessories

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- DSP254B Large LED wall display
- DSP506B Large LED wall display
- DSP704B Large LED wall display
- RYG11ABBK Red-yellow-green indicator lamps

If you have a Crestron, AMX, RCI or PC, use the RS232 adapter

- PS422DB9A0 RS232 to RS422 converter.