

# DSP104B-RYG-RF2



## Product

Wireless LED 1" Digit Display RYG lamps

### Description:

Wireless 2.4GHz Four-Digit Display, 1" High Digits, Solid-Segments and Red-Yellow-Green lamps.

**Item:** DSP104B-RYG-RF2

**UPC:** 788581651315

**EAN:** 0788581651315

**Stock Status:** Usually in stock.

**Dimensions:** 7" x 2.5" x 2.75"

**Weight:** 2.5 lbs.

**MSRP:** \$499.00

## Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- RJ11 modular connector for remote Start, Stop and Reset inputs.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 50mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.
- DSP104B Dimensions: 11" x 4.5" x 2.5".

## Features

- Count Up Timer with ground closure inputs or optional Start, Stop and Reset buttons.
- Digital Counter with ground closure inputs or optional Next (Increment), Previous (Decrement) and Reset buttons.
- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Four-digit count up timer settable to Day:Hour, Hour:Min, Min:Sec or Sec.Hundredths.
- Four-digit count down timer settable to Day:Hour, Hour:Min or Min:Sec.

## In the Box

- DSP104B-RF2 Wireless Large LED display
- WT12VAC1200MA-RA 12V AC, 1200mA transformer
- RC Reference card
- WD Wiring diagram

## Required Accessories

Choose one of the following controllers or keypads.

- TMR225B8-RF2 Wireless Count up/down timer with four-digit LED display 8 buttons and a knob.
- TMR216B-RF2 Wireless Count up/down timer with six-digit LED display 18 buttons and a knob.
- KP219A-RF2 Wireless 18-button keypad with knob

## Optional Accessories

Connect any optional accessory that has a wireless receiver. Examples:

- DSP504B-RF2 Wireless Wall display with five inch high digits
- RYG14AB-RF2 Green-Yellow-Red Indicator lamp module with wireless transceiver.