

# DSP256B-U



## Product

Six-Digit 2-1/3" Display Race Clock

### Description:

Six-Digit Race Clock, 2-1/3" High Digits, Solid-Segments, Integrated Count Up Timer with Lap Display, Remote Keypad, Metal Frame - Includes Infrared remote and Power Supply.

**Item:** DSP256B-U

**UPC:** 788581651919

**EAN:** 0788581651919

**Stock Status:** Usually in stock.

**Dimensions:** 15" x 4.5" x 2.25"

**Weight:** 4.5 lbs.

**MSRP:** \$549.00

## Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- RJ11 modular connector for remote Start, Stop and Reset inputs.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 70mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

## Features

- Convenience is important to most people. This gives you an advantage as Alzatex products are easy to use. The real benefit to you is a very quick learning curve.
- Count Up Timer with ground closure inputs or optional Start, Stop and Reset buttons.
- Digital Counter with ground closure inputs or optional Next (Increment), Previous (Decrement) and Reset buttons.
- LED seven-segment display with 2.33 inch high digits.
- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Six-digit count up timer settable to Day:Hour:Min, Hour:Min:Sec, or Min:Sec.Hundredths.

## In the Box

- DSP256B Display with count up/down timer with loud beeper.
- KP04B-SSR Keypad with three buttons.
- M6C007F RJ12, Six conductor standard phone cord, 7ft.
- WT12VAC1200MA-RA 12V AC, 1200mA transformer
- RC Reference guide
- WD Wiring diagram