

# DSP404B



## Product

Four-digit LED Display 4" Digits

### Description:

Four-Digit Display, 4" High Digits, Red LEDs, Metal Frame.

**Item:** DSP404B

**UPC:** 788581654606

**EAN:** 0788581654606

**Stock Status:** Special order item. Allow 6 weeks lead time.

**Dimensions:** 16" x 8" x 2.5"

**Weight:** 5.3 lbs.

**MSRP:** \$399.00

## Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- RJ11 modular connector for remote Start, Stop and Reset inputs.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 140mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.
- DSP404B Dimensions: 16" x 8" x 2.5".

## Features

- Convenience is important to most people. This gives you an advantage as Alzatex products are easy to use. The real benefit to you is a very quick learning curve.
- Count Up Timer with ground closure inputs or optional Start, Stop and Reset buttons.

- Digital Counter with ground closure inputs or optional Next (Increment), Previous (Decrement) and Reset buttons.
- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Four-digit count up timer settable to Day:Hour, Hour:Min, Min:Sec or Sec.Hundredths.
- Four-digit count down timer settable to Day:Hour, Hour:Min or Min:Sec.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 150mA maximum per digit.
- Construction: Light metal enclosure with transparent red acrylic front.

## Features with optional button module

- Count Up Timer.
- Count Down Timer. (0 to 99.59 MM:SS or 0 to 99:59:59 HH:MM:SS).
- User-programmable stored settings.
- Built-in time-of-day clock displays hours/minutes in 12/24 hour time or minutes/seconds.

## In the Box

- DSP404B Wall display
- RC Reference guide
- WD Wiring diagram
- M8BK003F Cable, 3ft, Cat-5
- Not Included: Keypad, transformer

## Required Accessories

- WT12VAC1200MA-RA 12V AC, 1200mA transformer

## Optional Accessories

- KP215ASM 8-button keypad with knob.
- ADD-BEEP Add 85dB beeper to display.