

# TMR106B6-SM



## Product

Clock/Timer 6 Digits

### Description:

Surface-mount Count Up/Down Timer with time-of-day clock, six-digit LED Display with 1" high red digits, stored presets, and Red-Yellow-Green LEDs.

**Item:** TMR106B6-SM

**UPC:** 788581652275

**EAN:** 0788581652275

**Stock Status:** Usually in stock.

**Dimensions:** 8.75" x 3" x 2.75"

**Weight:** 2 lbs.

**MSRP:** \$595.00

## Specifications

- Two RJ45 modular connectors for accessories.
- RJ11 modular connector for remote Start, Stop and Reset inputs.
- Ground closure 200mA output for optional beeper. (not included).
- Construction: Metal enclosure, black powder coated finish.
- Power requirements: 10-18 VAC or 12-24 VDC power.
- Current consumption: 200ma.

## Features

- Easy to use. Press Reset. Turn knob to set the desired time. Press Start.
- Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.
- Count Up elapsed Timer.
- Count Down time remaining Timer.
- User-programmable stored settings.
- 0-99.59.59 HH:MM:SS or 0-99:59 MM:SS.
- User-programmable Green, Yellow and Red warning Indicators.
- The Select button selects between setting hours, minutes and seconds.
- The Mode button selects between Count Up and Count Down modes. You may change between Count Up and Count Down modes while the timer is running. In Count Down mode, the timer stops when it reaches zero. In Count Up mode, the timer keeps running when the preset time is reached.
- Six-digit LED seven-segment Display with 1" high red digits.
- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Six-digit count up timer settable to Hour:Min:Sec.
- Six-digit count down timer settable to Hour:Min:Sec.
- Made of ruggedized aluminum construction.
- May be wall mounted or table top mounted.
- Includes swivel bracket for setting the viewing angle.

## In the Box

- TMR106B6-SM Six digit Count up/down timer with 1" high red digits.
- RC Reference guide
- WD Wiring diagram
- M8BK003F Cable, 3ft, Cat-5
- Not Included: Transformer

## Required Accessories

- WT12VAC1200MA-RA 12V AC, 1200mA transformer

## Optional Accessories

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- DSP254B Large LED wall display
- DSP506B Large LED wall display
- DSP704B Large LED wall display
- RYG11ABBK Red-yellow-green indicator lamps

If you have a Crestron, AMX, RCI or PC, use the RS232 adapter

- PS422DB9A0 RS232 to RS422 converter.