

# ALZW12A



## Product

Multi-Window Take-a-Number System

### Description:

This take-a-number package includes two wireless buttons, a 5-digit lobby display with 5" high digits and counter stand. The display indicates the ticket number and the window number. An indicator lamp over each window flashes to indicate which window is being served.

**Item:** ALZW12A

**UPC:** 788581657232

**EAN:** 0788581657232

**Dimensions:** 26" x 16" x 16"

**Weight:** 35.13 lbs.

**MSRP:** \$2,000.00

## Specifications

- (1) Two RJ45 modular connectors for RS422 serial data transmission and reception.
- (1) Two RJ11 modular connectors for accessories.
- (1) RJ11 modular connector for remote button inputs.
- (1) Power connector (2.1x5.5mm).
- (1) Test button for testing and configuration.
- (1) Power requirements: 10-15VAC or 12-20VDC.
- (1) Current consumption: 100mA maximum per digit.

- (1) Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

## Features

- (1) 5-digit 5" LED display showing Now Serving ticket number and Window to be served.
- (1) Standard mounting is 2 key hole slots spaced 9 inches apart for wall mounting.
- (1) There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.
- (1) There is one 1/4-20 nut on the bottom of the unit for attaching camera style tripod.
- (1) Wireless remote with two buttons.
- (1) Counter stand for ticket dispenser.
- (1) Add additional displays using cat-5 cable.

## Item Includes

One display included, multiple may be used:

- (1) DSP505B-NSW Large LED display

One of each of the following is required for each window (two included):

- (2) RFDXT21 Two-Button RF Transmitter.
- (2) NL16AG Indicator Lamp.

All systems include the following items:

- (1) RFDX1508 RF 8 Channel Receiver.
- (1) RGC16B-TAT TAT Sys Main Control Module.
- (1) DD210A-8B Lamp driver module with 8 outputs.
- (1) TMS3110 Ticket Dispenser Head.
- (1) TMS3115 Ticket Dispenser Counter Stand.
- (1) TMS3114 Take-A-Number Sign.
- (1) TMS3301X1 Three-Digit Ticket Roll.
- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer
- (1) RC Reference card
- (1) WD Wiring diagram