

# OR-DS505NSW-4MW-MP3



OR-DS505NSW-4MW-MP3  
Multi-Window Take-a-Number System with Voice Announce

## Product

Multi-Window Take-a-Number System

### Description:

This take-a-number package includes four hard-wired buttons, a 5-digit lobby display with 5" high digits, four IR remotes. The display indicates the ticket number and the window number.

**Item:** OR-DS505NSW-4MW-MP3

**UPC:** 788581658154

**EAN:** 0788581658154

**Dimensions:** 52" x 16" x 16"

**Weight:** 40.69 lbs.

**MSRP:** \$1,995.00

## Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- RJ11 modular connector for remote button inputs.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 100mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

## Features

- Convenience is important to most people. This gives you an advantage as Alzatex products are easy to use. The real benefit to you is a very quick learning curve.

- 5-digit 5" LED display showing Now Serving ticket number and Window to be served.
- Increases employee productivity by removing customer serving-order issues and stress.
- Wide viewing angle, 150 degree.
- Matched brightness LEDs for even display enhances readability.
- Easy to install CAT-5 cable to link multiple displays for multiple display applications.
- Power and data is carried over the CAT-5 cable in multiple display applications eliminating the need for multiple power supplies.
- Safe, low-voltage UL approved power supply.

## In the Box

One display included, multiple may be used:

- DSP505B-NSW Large LED display
- DC420A-MP3 Voice Announce accessory plays MP3 files.
- SP50WPS 5 1/4" 2-way indoor/outdoor speaker.
- M2C18G020F 20ft, 18ga, 2-conductor wire.
- (4) PB1-WH White push button
- (4) IR-27 IR remote control.
- M2C22G100F 100ft, 22ga, 2-conductor wire.
- TMS3110 Ticket Dispenser Head.
- TMS3115 Ticket Dispenser Counter Stand.
- TMS3114 Take-A-Number Sign.
- TMS3301X1 Three-Digit Ticket Roll.
- M8BK007F 7ft, Cat-5, 8-conductor cable.
- WT12VAC1200MA-RA 12V AC, 1200mA transformer
- RC Reference guide
- WD Wiring diagram

For windows five through sixteen:

- RGC16B-TAT Sys Main Control Module.