

TMR225B8-RF2



Product

Wireless Clock/Timer, 4 Digits

Description:

Wireless 2.4GHz Surface-mount Count Up/Down Timer with time-of-day clock, 4-digit LED Display, 3 stored presets, and Red-Yellow-Green LEDs.

Item: TMR225B8-RF2

UPC: 788581659656

EAN: 0788581659656

Stock Status: Usually in stock.

Dimensions: 4.5" x 4.5" x 2.65"

Weight: 1 lbs.

MSRP: \$645.00

Specifications

- Two CAT-5 connectors for accessories.
- RJ11 modular connector for remote Start, Stop and Reset inputs.
- Ground closure 200mA output for optional beeper. (not included).
- Ground closure input.
- Construction: Metal enclosure, black powder coated finish.

- Power requirements: 10-18 VAC or 12-24 VDC power.
- Current consumption: 100ma.

Features

- Easy to use. Press Reset. Turn knob to set the desired time. Press Start.
- Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.
- Count Up elapsed Timer.
- Count Down time remaining Timer.
- Up to 3 user-programmable stored settings.
- 0-99.59 MM:SS or 0-99:59 HH:MM.
- User-programmable Green, Yellow and Red warning Indicators.
- The Select button selects between setting hours, minutes and seconds.
- The Mode button selects between Count Up and Count Down modes. You may change between Count Up and Count Down modes while the timer is running. In Count Down mode, the timer stops when it reaches zero. In Count Up mode, the timer keeps running when the preset time is reached.
- Four-digit LED seven-segment Display with 0.56" high digits.
- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Four-digit count up timer settable to Hour:Min or Min:Sec.
- Four-digit count down timer settable to Hour:Min or Min:Sec.
- Made of ruggedized aluminum construction.

In the Box

- TMR225B8-RF2 Wireless Count up/down timer
- RC Reference card
- WD Wiring diagram
- WT12VAC1200MA-RA 12V AC, 1200mA transformer

Optional Accessories

Works with any size Wireless or wired Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- DSP254B Large LED wall display
- DSP506B Large LED wall display
- DSP704B Large LED wall display
- RYG14AB-RF2 Wireless Red-yellow-green indicator lamps

If you have a Crestron, AMX, RCI or PC, use the RS232 adapter

- PS422DB9 RS232 to RJ45 jack converter