# ALZM07A





# Product

Presentation Timer w/ Large LED Display

#### **Description:**

This wireless presentation TimeKeeper<sup>™</sup> system includes a TMR218B6 Count Up/Down Timer with two programmable presets, and a DSP504B Large Four-digit LED wall Display visible (up to 100ft) to the speaker and the audience.

Item: ALZM07A

UPC: 788581650073

EAN: 0788581650073

Stock Status: Obsolete.

Dimensions: 21.5" x 8" x 2.5"

Weight: 9.2 lbs.

MSRP: \$1,299.00

# **Specifications**

• (1) Two Serial data RJ11 connectors for accessories.

• (1) One RS422 output with RJ45 connector for accessories.

• (1) Ground closure 600mA output for optional beeper. (not included).

- (1) Timer Construction: ABS Plastic enclosure, black.
- (1) Display Construction: Metal enclosure, black powder coated finish.

• (1) Power requirements: 10-18 VAC or 12-24 VDC power.

- (1) Current consumption: 500ma.
- (1) TMR218B6BK\_RF2 Dimensions: 6.75" x 4.75" x 2.5".
- (1) DSP504B Dimensions: 21.5" x 8" x 2.5".

#### **Mounting methods**

• (1) Standard mounting is 2 key hole slots spaced 16"es apart for wall mounting.

• (1) There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.

• (1) 1/4-20 nuts on the bottom of the unit for attaching a tripod adapter or feet. The feet and tripod adapter is NOT included and may be ordered separately.

• (1) The display has holes in the top for adding a handle. The handle is NOT included and may be ordered separately.

### **Features**

- (1) Count up elapsed timer settable to Hour:Min or Min:Sec.
- (1) Count down time remaining timer settable to Hour:Min or Min:Sec.
- (1) Easy to use. Press Reset. Turn knob to set the desired time. Press Start.

• (1) Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.

• (1) Green, Yellow and Red warning indicators have preprogrammed settings to match Toastmasters requirements, or may be programmed by user.

• (1) Four-digit LED seven-segment Display with 0.56" high digits.

• (1) Beeper provides audible sound when timer reaches zero.

- (1) Button to turn beeper on/off.
- (1) Connect two or more TimeKeepers<sup>™</sup> together.

One becomes the timer, and the others become remote displays.

• (1) Made of ruggedized aluminum construction.

## **Item Includes**

- (1) TMR218B6BK-RF2 Wireless Count up/down timer.
- (1) DSP504B Large LED display
- (1) ADD-RF-MX04A RF 2.4GHZ Transceiver, for top of display.
- (2) WT12VAC1200MA-RA 12V AC, 1200mA transformer
- (1) RC Reference card
- (1) WD Wiring diagram

## **Optional Accessories**

- (1) RYG11ABBK Red-yellow-green indicator lamps
- (1) RYG472AB Red-yellow-green indicator lamps



