

# ALZW08C



## Product

Multi-Window Take-a-Number System

### Description:

This take-a-number package includes two wireless window service terminals, 5-digit lobby display with 5" high digits, window displays and floor stand. The display indicates the ticket number and the window number.

**Item:** ALZW08C

**UPC:** 788581654651

**EAN:** 0788581654651

**Dimensions:** 52" x 16" x 16"

**Weight:** 43.81 lbs.

**MSRP:** \$3,242.00

## Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- RJ11 modular connector for remote button inputs.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 100mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

## Features

- 5-digit 5" LED display showing Now Serving ticket number.
- Standard mounting is 2 key hole slots spaced 9 inches apart for wall mounting.

- There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.
- There is one 1/4-20 nut on the bottom of the unit for attaching camera style tripod.
- Each window has a 4-digit display window terminal.
- Floor stand for ticket dispenser.

## In the Box

One display included, multiple may be used:

- DSP505B-NSW Large LED display

One of each of the following are required for each window:

- (2) DSP104A-TAT-RF900 Wireless Window Terminal.
- (2) DSP253B-RF900 2-1/3" Three-Digit Display.
- (2) LB01A Magnetic Sign.

All systems include the following items:

- RF900A-TAT RF Wireless Transceiver
- TMS3110 Ticket Dispenser Head.
- TMS3113 Ticket Dispenser Floor Stand.
- TMS3114 Take-A-Number Sign.
- TMS3301X1 Three-Digit Ticket Roll.
- (5) WT12VAC1200MA-RA 12V AC, 1200mA transformer
- RC Reference guide
- WD Wiring diagram