

ALZW16A



ALZW16A - Multi-Window Take-a-Number System

Product

Multi-Window Take-a-Number System

Description:

This waiting line management package includes wireless buttons and a 3-digit Display with 5" high digits.

Item: ALZW16A

UPC: 788581657270

EAN: 0788581657270

Dimensions: 52" x 16" x 16"

Weight: 30.51 lbs.

MSRP: \$1,283.00

Specifications

- (1) Two RJ45 modular connectors for RS422 serial data transmission and reception.
- (1) Two RJ11 modular connectors for accessories.
- (1) RJ11 modular connector for remote button inputs.
- (1) Power connector (2.1x5.5mm).
- (1) Test button for testing and configuration.
- (1) Power requirements: 10-15VAC or 12-20VDC.
- (1) Current consumption: 100mA maximum per digit.
- (1) Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

Features

- (1) Three-Digit 5" LED display showing Now Serving ticket number.

- (1) Standard mounting is 2 key hole slots spaced 9 inches apart for wall mounting.
- (1) There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.
- (1) There is one 1/4-20 nut on the bottom of the unit for attaching camera style tripod.
- (1) Each window has a wireless 4-digit display with (Next-Previous-Reset) buttons.
- (1) Floor stand for ticket dispenser.
- (1) Add additional displays using cat-5 cable.

Item Includes

One display included, multiple may be used:

- (1) DSP503B-NS Large LED display

One of each of the following are required for each window:

- (1) DSP104A-NPR-RF900 Small Wireless Display w/ 3-Buttons.

One wireless module is required for each large display.

- (1) RF900A RF Wireless Transceiver

All systems include the following items:

- (1) TMS3110 Ticket Dispenser Head.
- (1) TMS3113 Ticket Dispenser Floor Stand.
- (1) TMS3114 Take-A-Number Sign.
- (1) TMS3301X1 Three-Digit Ticket Roll.
- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer
- (1) RC Reference card
- (1) WD Wiring diagram