

# DC117B6-WAIT1



## Product

Take-A-Number Controller with sd memory

### Description:

Take-A-Number PRO Ticket Printer Controller with SD Card Memory - Customization Available.

**Item:** DC117B6-WAIT1

**UPC:** 788581652695

**EAN:** 0788581652695

**Stock Status:** Usually in stock.

**Dimensions:** 6.35" x 3.75" x 2.31"

**Weight:** 1.2 lbs.

**MSRP:** \$695.00

## Specifications

- (1) Two RJ45 modular connectors for RS422 serial data transmission and reception.
- (1) RJ11 modular connector for remote Start, Stop and Reset inputs.
- (1) Power requirements: 10-18 VAC or 12-24 VDC power.
- (1) Display: Backlit LCD Display with 4 lines of 20 characters.
- (1) Current consumption: 480MA max.
- (1) Construction: Metal enclosure, black powder coated finish.
- (1) DC117B6\_WAIT1 Dimensions: 6.4" x 3.7" x 2.5".

## Features

- (1) Each time a ticket is printed, the ticket number, type of service requested, time and date are recorded.

- (1) The Next button increments the Display to the next number, records the ticket number, window being served, time and date.
- (1) Integrated data capture of wait times holds up to 4000 events.
- (1) Every transaction is time stamped so that complete data analysis can be performed.
- (1) An unlimited number of events can be recorded on the integrated SD memory card.
- (1) The results can later be analyzed. Charts and graphs can be generated from the data.

## Item Includes

- (1) DC117B6-WAIT1 Take-a-number system controller
- (1) RC Reference card
- (1) WD Wiring diagram
- (1) M8BK003F Cable, 3ft, Cat-5
- (1) Not Included: Transformer

## Required Accessories

- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer
- (1) KTP7X422A-8B Take-a-number system interface module.

## Optional Accessories

- (1) DSP502B-NS Large LED wall display
- (1) DSP503B-NS Large LED wall display
- (1) DSP504B-NSW Large LED wall display
- (1) DSP505B-NSW Large LED wall display