

DC420A-MP3



Product

Voice Announce accessory plays MP3 files

Description:

Voice announce accessory to play voice announce messages over PA speakers.

Item: DC420A-MP3

UPC: 788581653241

EAN: 0788581653241

Stock Status: Usually in stock.

Dimensions: 5.7" x 4.5" x 2"

Weight: 1.2 lbs.

MSRP: \$1,450.00

Specifications

- Built in 15W Audio amplifier with Speaker output for 2 speakers.
- Audio line output for driving external audio amplifier.
- Power requirements for 5 watt per channel output: 10-16 VAC or 12-18 VDC power.
- Power requirements for 15 watt per channel output: 24VAC or 36VDC power.
- Current consumption: 1500MA max.
- Construction: Metal enclosure, black powder coated finish.
- DC420A_MP3 Dimensions: 5.7" x 4.5" x 2.0".

Features

- Plays voice announce messages "Now serving number 23 at window number 4".
- Plays voice announce messages "Now serving number 46 at the hot deli".
- Custom voice messages.
- Can be used with any language.

In the Box

- DC420A-MP3 Voice announce accessory for DC410A, DC410A or DC417A.
- RC Reference guide
- WD Wiring diagram
- M8BK003F Cable, 3ft, Cat-5
- Not Included: Power supply.
- 1840382 4Pin 3.5mm 180Degree, Phoenix Contact Pluggable Mini Terminal Block.

Required Accessories

The DC420A-MP3 is a module is connected to a DC410A, DC410A or DC417A controller.

- DC410A Take-a-number system controller
- DC410A Take-a-number system controller
- DC417A Take-a-number system controller

You can install speakers or send the output of the DC420A-MP3 to a paging system or other external audio amplifier.

- (2) SP50WPS 5 1/4" 2-way indoor/outdoor speaker

Optional Accessories

- RF9 Wireless module, 900mHz.
- 24VAC power supply or 36VDC power supply to boost wattage to 15 watts per channel.
- Extended maintenance agreement. The extended maintenance agreement includes free software updates. Contact Alzatex for details.