

# RYG13A



- Green-Talk; Yellow-Wrap it up; Red-Done LED Indicators.

## In the Box

- RYG13A Indicator lamp module
- RC Reference guide
- WD Wiring diagram
- M4C007F 7ft 4-conductor standard modular phone cord.
- Not Included: Transformer

## Product

Flush Mount Red-Yellow-Green Indicator

### Description:

Flush-mount Red-Yellow-Green unit, 1/2" diameter dome LEDs without beeper (black metal plate).

**Item:** RYG13A

**UPC:** 788581651247

**EAN:** 0788581651247

**Stock Status:** Usually in stock.

**Dimensions:** 5" x 2.5" x 1.5"

**Weight:** 0.5 lbs.

**MSRP:** \$189.00

## Specifications

- RJ45 modular connector for RS422 serial data input.
- RJ11 modular connectors for serial data input.
- Solder terminals for optional loud beeper.
- Construction: Metal flush mount plate, black powder coated finish.
- Power requirements: 10-13VAC or 12-15VDC.
- Current consumption: 100mA.

## Features

- Flush Mount Red-Yellow-Green Indicator.
- Red-Yellow-Green Audience signal lights.
- Works with The TimeKeeper™, Alzatex, Inc.'s zero to 99.59 minute Count Up/Down Timers.
- May be powered using AC or DC power.
- Low power consumption.
- Optional built-in internal beeper. The Count Up/Down TimeKeeper™ can enable or disable the beeper.