

RYG200AB



Product

Red-Yellow-Green signal lights, 2"

Description:

Large Red-Yellow-Green unit with 2"x2" LED clusters, manual controlled input controlled by ground closure or external buttons and loud beeper. (Metal Enclosure).

Item: RYG200AB

UPC: 788581651285

EAN: 0788581651285

Stock Status: Usually in stock.

Dimensions: 11" x 4.5" x 2.5"

Weight: 2.35 lbs.

MSRP: \$365.00

Specifications

- RJ45 modular connector for RS422 serial data input.
- RJ11 modular connectors for serial data input.
- Ground closure inputs to manually operate the Green, Yellow, Red Indicators and the beeper.
- Power connector (2.1x5.5mm).
- Screw terminal connector for loud beeper.
- Screw terminal connector for 8 ohm speaker.
- Construction: Metal enclosure, black powder coated finish.
- Power requirements: 10-13VAC or 12-15VDC.
- Current consumption: 250mA.

Features

- Red-Yellow-Green Audience signal lights.
- Works with The TimeKeeper™, Alzatex, Inc.'s zero to 99.59 minute Count Up/Down Timers.
- May be powered using AC or DC power.

- Low power consumption.
- Optional built-in internal beeper. The Count Up/Down TimeKeeper™ can enable or disable the beeper.
- Green-Talk; Yellow-Wrap it up; Red-Done LED Indicators.
- The Wall Mount or portable Red-Yellow-Green Indicator is available with black or OAK enclosure.
- Audio output (2 watt) for a speaker, that will generate user-programmable audible tones.

In the Box

- RYG200AB Red-Yellow-Green Indicator lamp module.
- RC Reference guide
- WD Wiring diagram
- M8BK007F Cable, 7ft, CAT-5
- Not Included: Transformer