

# SPE602S



- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 150mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

## Features

- Two-Digit count up timer settable to Day, Hour, Min or Sec.
- Two-Digit count down timer settable to Day, Hour, Min or Sec.

## Item Includes

- (1) DSP602S Large LED Display.
- (1) KP215ASM Remote Keypad.
- (1) M8BK025F Cable, 25ft, Cat-5.
- (1) WTSP24W150 15VDC 1.6A Wall Adapter
- (1) RC Reference card.
- (1) WD Wiring diagram.

## Product

Digital LED Sports Display, 6" Digits

### Description:

Two-digit Race Clock with 6 inch high super bright red LED digits for sporting events, with handle, feet, water resistant enclosure, Metal frame. Includes remote keypad, connection cable and power supply.

**Item:** SPE602S

**UPC:** 788581655177

**EAN:** 0788581655177

**Stock Status:** Usually in stock.

**Dimensions:** 13.0" x 10.5" x 2.5"

**Weight:** 24.4 lbs.

**MSRP:** \$1,134.00

## Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- Power connector (2.1x5.5mm).