

# SPE602SSW



- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 150mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

## Features:

- Two-Digit count up timer settable to Day, Hour, Min or Sec.
- Two-Digit count down timer settable to Day, Hour, Min or Sec.

## Item Includes:

- (1) DSP602SSW Large LED Display.
- (1) KP219A-RF2 Wireless Keypad.
- (1) WTPS24W150 15VDC 1.6A Wall Adapter
- (1) RC Reference card.
- (1) WD Wiring diagram.

## Product

Digital LED Display, 6in High Digits

### Description:

Two-digit Race Clock with 6 inch high super bright red LED digits for sporting events, with an internal RF Wireless Transceiver, integrated gell cell battery and charger, handle, feet, water resistant enclosure, Metal frame. Includes wireless keypad, power supply.

**Item:** SPE602SSW

**UPC:** 788581655290

**EAN:** 0788581655290

**Stock Status:** Usually in stock.

**Dimensions:** 13.0" x 10.5" x 2.5"

**Weight:** 24.4 lbs.

**MSRP:** \$1,794.00

## Specifications:

- Two RJ45 modular connectors for RS422 serial data transmission and reception.