

ALZA001A



Product

LED Arcade Timer Display.

Description:

Four-Digit Arcade Timer Package.

Item: ALZA001A

UPC: 788581653401

EAN: 0788581653401

Stock Status: Usually in stock.

Dimensions: 11.125" x 4.75" x 2.125"

Weight: 5.1 lbs.

MSRP: \$597.00

Specifications

- (1) Two RSSR modular connectors for remote Start, Stop and Reset inputs.
- (1) Power connector (2.1x5.5mm).
- (1) Test button for testing and configuration.
- (1) Power requirements: 10-15VAC or 12-20VDC.
- (1) Current consumption: 80mA maximum per digit.
- (1) Construction: Display in metal enclosure, black powder coated finish with transparent red acrylic front.
- (1) Construction: Arcade Buttons in hard plastic enclosure.
- (1) DSP254B Dimensions: 11.125" x 4.75" x 2.125".
- (1) Arcade Button Enclosure Dimensions: 5.5" x 4.75" x 3.25".

Features

- (1) Count Up Arcade Timer with Two RSSR ports for the Start and Stop Arcade buttons.
- (1) Preconfigured for "Plug-n-play" convenience.
- (1) Display has a loud internal beeper (Beeper mode can be changed via the IR remote).
- (1) Green Arcade Button has a small RESET on the side of the enclosure.
- (1) Arcade Buttons light up

Item Includes

- (1) DSP254B Large LED display
- (1) DSP504B Large LED display
- (1) DSP704B Large LED display
- (1) Green arcade button in plastic enclosure
- (1) Red arcade button in plastic enclosure
- (1) M4C050F 50ft 4-pin standard phone cables
- (1) Mounting screws for display
- (1) IR27A IR remote for menu navigation
- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer
- (1) RC Reference card
- (1) WD Wiring diagram