

# ALZM09A



## Product

Presentation Timer w/ Large LED Display

### Description:

This wireless presentation TimeKeeper™ system includes a TMR218B6 Count Up/Down Timer with two programmable presets, and a DSP704B Large Four-digit LED wall Display visible (up to 200ft) to the speaker and the audience.

**Item:** ALZM09A

**UPC:** 788581650097

**EAN:** 0788581650097

**Stock Status:** Obsolete.

**Dimensions:** 26" x 10.5" x 2.5"

**Weight:** 17.4 lbs.

**MSRP:** \$1,799.00

## Specifications

- (1) Two Serial data RJ11 connectors for accessories.
- (1) One RS422 output with RJ45 connector for accessories.
- (1) Ground closure 600mA output for optional beeper. (not included).
- (1) Timer Construction: ABS Plastic enclosure, black.
- (1) Display Construction: Metal enclosure, black powder coated finish.
- (1) Power requirements: 10-18 VAC or 12-24 VDC power.

- (1) Current consumption: 900ma.
- (1) TMR218B6BK\_RF2 Dimensions: 6.75" x 4.75" x 2.5".
- (1) DSP704B Dimensions: 25.5" x 10.5" x 2.5".

## Features

- (1) Count up elapsed timer settable to Hour:Min or Min:Sec.
- (1) Count down time remaining timer settable to Hour:Min or Min:Sec.
- (1) Easy to use. Press Reset. Turn knob to set the desired time. Press Start.
- (1) Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.
- (1) Green, Yellow and Red warning indicators have preprogrammed settings to match Toastmasters requirements, or may be programmed by user.
- (1) Four-digit LED seven-segment Display with 0.56" high digits.
- (1) Beeper provides audible sound when timer reaches zero.
- (1) Button to turn beeper on/off.
- (1) Built in Time of day clock displays 12 or 24 hour mode.
- (1) Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- (1) Made of ruggedized aluminum construction.

## Item Includes

- (1) TMR218B6BK-RF2 Wireless Count up/down timer.
- (1) DSP704B Large LED display
- (1) ADD-RF-MX04A RF 2.4GHZ Transceiver, for top of display.
- (2) WT12VAC1200MA-RA 12V AC, 1200mA transformer
- (1) RC Reference card
- (1) WD Wiring diagram

## Optional Accessories

- (1) RYG11AB BK Red-yellow-green indicator lamps
- (1) RYG472AB Red-yellow-green indicator lamps