

DSP106B0



Product

6-Digit LED Display 1" Digits

Description:

Six-Digit Display with 1" High Solid-Segment Digits with swivel bracket.

Item: DSP106B0

UPC: 788581651377

EAN: 0788581651377

Stock Status: Usually in stock.

Dimensions: 8.5" x 3" x 2.75"

Weight: 1.5 lbs.

MSRP: \$349.00

Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- Ground closure inputs to remotely start, stop or reset the timer.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 240mA max.
- Construction: Metal enclosure, black powder coated finish.

Features

- Count Up Timer with ground closure inputs or optional Start, Stop and Reset buttons.
- Digital Counter with ground closure inputs or optional Next (Increment), Previous (Decrement) and Reset buttons.
- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Six-digit count up timer settable to Day:Hour:Min, Hour:Min:Sec, or Min:Sec.Hundredths.
- Six-digit count down timer settable to Day:Hour:Min, Hour:Min:Sec.

In the Box

- DSP106B 6 digit LED Display.
- RC Reference guide
- WD Wiring diagram
- M8BK007F Cable, 7ft, CAT-5
- Not Included: Keypad, transformer