

DSP204B5



Product

Display with 2.5" high LED digits

Description:

Four-Digit Display, 2.5" High Digits, Red LEDs, Time-of-Day Clock, Metal Enclosure - Power Supply not Included.

Item: DSP204B5

UPC: 788581654385

EAN: 0788581654385

Stock Status: Clearance Item. This product will be deleted once stock is gone.

Dimensions: 11" x 5" x 2"

Weight: 2.42 lbs.

MSRP: \$399.00

Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- Ground closure inputs to remotely start, stop or reset the timer.
- Solder connections for an optional loud beeper.
- Optional SPDT Beep relay output.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 150mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

Features

- Built-in time-of-day clock displays hours/minutes in 12/24 hour time or minutes/seconds.

- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Four-digit count up timer settable to Day:Hour, Hour:Min, Min:Sec or Sec.Hundredths.
- Four-digit count down timer settable to Day:Hour, Hour:Min or Min:Sec.

Features with optional keypad

- Count Up Timer.
- Count Down Timer. (0 to 99.59 MM:SS or 0 to 99:59:59 HH:MM:SS).
- User-programmable stored settings.
- Built-in time-of-day clock displays hours/minutes in 12/24 hour time or minutes/seconds.
- Button to turn beeper on/off.

In the Box

- DSP204B5 LED display with integrated Count up/down timer.
- RC Reference guide
- WD Wiring diagram
- Not Included: Transformer, cables

Required Accessories

- WT12VAC1200MA-RA 12V AC, 1200mA transformer

Optional Accessories

- DSP254B Large LED wall display
- RYG11ABBK Red-yellow-green indicator lamps