DSP254X2B



Product

Dual LED 2-1/3" Digits Display

Description:

Four-Digit Display, 2-1/3" High Digits, Solid-Segments, Metal Frame.

Item: DSP254X2B

UPC: 788581652473

EAN: 0788581652473

Stock Status: Usually in stock.

Dimensions: 24" x 6" x 2.5"

Weight: 8.9 lbs. **MSRP:** \$598.00

Specifications

- (1) Two RJ45 modular connectors for RS422 serial data transmission and reception.
- (1) Two RJ11 modular connectors for accessories.
- (1) RJ11 modular connector for remote Start, Stop and Reset inputs.
- (1) Power connector (2.1x5.5mm).
- (1) Test button for testing and configuration.
- (1) Power requirements: 10-15VAC or 12-20VDC.
- (1) Current consumption: 80mA maximum per digit.
- (1) Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.
- (1) Dual DSP254B displays in a common enclosure.
- (1) Includes Loud Beeper.
- (1) DSP254X2B Dimensions: 24" x 6" x 2.5".

Features

- (1) Count Up Timer with ground closure inputs or optional Start, Stop and Reset buttons.
- (1) Digital Counter with ground closure inputs or optional Next (Increment), Previous (Decrement) and Reset buttons.

- (1) Connect two or more TimeKeepers[™] together. One becomes the timer, and the others become remote displays.
- (1) Four-digit count up timer settable to Day:Hour, Hour:Min, Min:Sec or Sec.Hundredths.
- (1) Four-digit count down timer settable to Day:Hour, Hour:Min or Min:Sec.

Item Includes

- (1) DSP254X2B Dual 4-Digit LED displays with 2-1/3" high digits in a common enclosure.
- (1) RC Reference card
- (1) WD Wiring diagram
- (1) M8BK003F Cable, 3ft, Cat-5
- (1) Not Included: Transformer

Required Accessories

- (1) WT12VAC20VA-RA Wall transformer
- (1) PS60W150 15VDC, 4A Power Supply with 6ft power cord

Optional Accessories

• (1) KP215ASM 8-button keypad with knob.



