

DSP256BT



Product

Six-Digit 2-1/3IN Display Tri-Color

Description:

Six-Digit Display, 2-1/3" High Digits, Solid-Segment Tricolor LEDs, Metal Frame.

Item: DSP256BT

UPC: 788581651483

EAN: 0788581651483

Stock Status: Usually in stock.

Dimensions: 15" x 4.5" x 2.25"

Weight: 3.9 lbs.

MSRP: \$399.00

Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- RJ11 modular connector for remote Start, Stop and Reset inputs.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 80mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with smoke grey acrylic front.

Features

- Count Up Timer with ground closure inputs or optional Start, Stop and Reset buttons.
- Digital Counter with ground closure inputs or optional Next (Increment), Previous (Decrement) and Reset buttons.

- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Six-digit count up timer settable to Day:Hour:Min, Hour:Min:Sec, or Min:Sec.Hundredths.
- Six-digit count down timer settable to Day:Hour:Min, Hour:Min:Sec.

In the Box

- DSP256B Large LED display
- RC Reference guide
- WD Wiring diagram
- M8BK003F Cable, 3ft, Cat-5
- Not Included: Transformer

Required Accessories

- WT12VAC1200MA-RA 12V AC, 1200mA transformer

Optional Accessories

- KP215ASM 8-button keypad with knob.
- WT12VAC1200MA-RA 12V AC, 1200mA transformer