

# DSP264BD



## Product

4-digit Up/Down timer, 2-1/3" digits

### Description:

Four-Digit Display, 2-1/3" High Digits, Solid-Segments, Integrated Count Down Timer with 2 Large Mushroom Buttons and 1 Knob in NEMA4X Enclosure.

**Item:** DSP264BD

**UPC:** 788581656754

**EAN:** 0788581656754

**Stock Status:** Allow 6 weeks lead time.

**Dimensions:** 13" x 5" x 3"

**Weight:** 6 lbs.

**MSRP:** \$549.00

## Specifications

- (1) One Optically coupled input resets and starts the timer.
- (1) One Optically coupled input stops the timer.
- (1) Two RJ45 modular connectors for RS422 serial data transmission and reception.
- (1) Power connector (2.1x5.5mm).
- (1) Test button for testing and configuration.
- (1) Power requirements: 10-15VAC or 12-20VDC.
- (1) Current consumption: 500mA max.
- (1) Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.
- (1) DSP264BD Dimensions: 13" x 5" x 3".
- (1) Mounting flanges add 0.75" on either end. Total length is 14.5".

## Features

- (1) Four-digit count up timer settable to Day:Hour, Hour:Min, Min:Sec or Sec.Hundredths.

- (1) Four-digit count down timer settable to Day:Hour, Hour:Min or Min:Sec.

## Item Includes

- (1) DSP264BD Large LED Display in NEMA4X enclosure with integrated count down timer.
- (1) RC Reference card
- (1) WD Wiring diagram
- (1) Not Included: Keypad, transformer, cables

## Required Accessories

- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer