# **DSP504B**





## **Product**

Four-digit LED Display 5" Digits

### **Description:**

Four-Digit Display, 5" High Digits, Red LEDs, Metal Frame.

Item: DSP504B

UPC: 788581651612

EAN: 0788581651612

Stock Status: Usually in stock.

**Dimensions:** 21.5" x 8" x 2.5"

**Weight:** 5.9 lbs. **MSRP:** \$495.00

## **Specifications**

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- RJ11 modular connector for remote Start, Stop and Reset inputs.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 100mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

### **Mounting methods**

- Standard mounting is 2 key hole slots spaced 16inch apart for wall mounting.
- There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.

- 1/4-20 nuts on the bottom of the unit for attaching a tripod adapter or feet. The feet and tripod adapter is NOT included and may be ordered separately.
- The display has holes in the top for adding a handle. The handle is NOT included and may be ordered separately.

### **Features**

- Four-digit count up timer settable to Day:Hour, Hour:Min, Min:Sec or Sec.Hundredths.
- Four-digit count down timer settable to Day:Hour, Hour:Min or Min:Sec.

#### In the Box

- DSP504B Wall display
- RC Reference guide
- WD Wiring diagram
- M8BK003F Cable, 3ft, Cat-5
- Not Included: Keypad, transformer



