

# DSP505B



## Product

Five-digit LED Display 5" Digits

### Description:

5-digit Display, 5" High Digits, Red LEDs, Metal Frame.

**Item:** DSP505B

**UPC:** 788581651643

**EAN:** 0788581651643

**Stock Status:** Usually in stock.

**Dimensions:** 21.5" x 8" x 2.5"

**Weight:** 6.2 lbs.

**MSRP:** \$560.00

## Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- RJ11 modular connector for remote Start, Stop and Reset inputs.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 100mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

### Mounting methods

- Standard mounting is 2 key hole slots spaced 16inch apart for wall mounting.
- There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.
- 1/4-20 nuts on the bottom of the unit for attaching a tripod adapter or feet. The feet and tripod adapter is NOT included and may be ordered separately.

- The display has holes in the top for adding a handle. The handle is NOT included and may be ordered separately.

## Features

- Six-digit count up timer settable to Day:Hour:Min, Hour:Min:Sec, or Min:Sec.Hundredths.
- Six-digit count down timer settable to Day:Hour:Min, Hour:Min:Sec.

## In the Box

- DSP505B Wall display
- RC Reference guide
- WD Wiring diagram
- M8BK003F Cable, 3ft, Cat-5
- Not Included: Keypad, transformer