

# DSP518A-LA



## Product

Last Accident Display 5" Digits

### Description:

Four-Digit Display with 5" High Digits and Red LEDs, Four-Digit Display with 1" High Digits, 2"x 2" LED Clusters, in Common Metal Enclosure for Display of "Days Since Last Accident".

**Item:** DSP518A-LA

**UPC:** 788581650448

**EAN:** 0788581650448

**Stock Status:** Usually in stock.

**Dimensions:** 21.5" x 8" x 2.5"

**Weight:** 6 lbs.

**MSRP:** \$1,049.00

## Specifications

- (1) Two RJ45 modular connectors for RS422 serial data transmission and reception.
- (1) Two RJ11 modular connectors for accessories.
- (1) RJ11 modular connector for remote Start, Stop and Reset inputs.
- (1) Power connector (2.1x5.5mm).
- (1) Test button for testing and configuration.
- (1) Power requirements: 10-15VAC or 12-20VDC.
- (1) Current consumption: 100mA maximum per digit.
- (1) Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

## Mounting methods

- (1) Standard mounting is 2 key hole slots spaced 16inch apart for wall mounting.
- (1) There are screws at either end of the displays where D-Rings can be added. D-Rings are NOT included and may be ordered separately.
- (1) 1/4-20 nuts on the bottom of the unit for attaching a tripod adapter or feet. The feet and tripod adapter is NOT included and may be ordered separately.
- (1) The display has holes in the top for adding a handle. The handle is NOT included and may be ordered separately.

## Features

- (1) Four-digit Large 5" LED Display shows days since last accident.
- (1) Four-digit Display with 1" high digits shows the time-of-day Clock in hours and minutes.
- (1) Green-Yellow-Red Display with 2"x2" LED clusters shows severity of the most recent accident.
- (1) Remote button plate to setup the time of day and the days since last accident.

## Item Includes

- (1) DSP518A-LA Lost time accident display.
- (1) KP215ASM Keypad with 8 buttons and a knob.
- (1) WT12VAC1200MA-RA 12V AC, 1200mA transformer
- (1) RC Reference card
- (1) WD Wiring diagram
- (1) Not Included: cables.