

# DSP604B



## Product

Four-Digit LED Display 6" Digits

### Description:

Four-Digit Display, 6" High Digits, Super Bright Red LEDs, Metal Frame.

**Item:** DSP604B

**UPC:** 788581651759

**EAN:** 0788581651759

**Stock Status:** Usually in stock.

**Dimensions:** 25" x 10.5" x 2.5"

**Weight:** 9.2 lbs.

**MSRP:** \$825.00

## Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 150mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

### Mounting methods

- Standard mounting is two D-rings, one at either end of the display.
- 1/4-20 nuts on the bottom of the unit for attaching feet or wall bracket. The feet or wall brackets are NOT included and may be ordered separately.
- The display has holes in the top for adding a handle. The handle is NOT included and may be ordered separately.

## Features

- Four-digit count up timer settable to Day:Hour, Hour:Min, Min:Sec or Sec.Hundredths.
- Four-digit count down timer settable to Day:Hour, Hour:Min or Min:Sec.

## In the Box

- DSP604B Large LED Wall Display.
- RC Reference guide
- WD Wiring diagram
- M8BK003F Cable, 3ft, Cat-5
- Not Included: Keypad, transformer

## Required Accessories

- KP215ASM Remote keypad
- M8BK025F Cable, 25ft, Cat-5
- WTPS24W150 15VDC 1.6A Wall Adapter