

# DSP7025S



- Current consumption: 200mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

## Features

- Two and a half Digit display for speeds from 0 to 199.

## In the Box

- DSP7025S Large LED Display with 7" high digits.
- WTPS24W150 15VDC 1.6A Wall Adapter
- RC Reference guide
- WD Wiring diagram
- Not Included: Cables

## Product

7 in. 2.5-Digit Radar Gun Readout

### Description:

2.5-Digit, 7" High display with Super Bright Red LEDs, Handle and Feet, Water Resistant Enclosure, Metal Frame.

**Item:** DSP7025S

**UPC:** 788581658055

**EAN:** 0788581658055

**Stock Status:** Allow 3 weeks for delivery.

**Dimensions:** 13" x 10.5" x 2.5"

**Weight:** 13.6 lbs.

**MSRP:** \$999.00

## Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.