DSP703B





Product

Three-Digit LED Display 7" Digits

Description:

Three-Digit Display, 7" High Digits, Super Bright Red LEDs, Metal Frame.

Item: DSP703B

UPC: 788581651780

EAN: 0788581651780

Stock Status: Usually in stock.

Dimensions: 18" x 10.5" x 2.5"

Weight: 13.6 lbs.

MSRP: \$895.00

Specifications

• Two RJ45 modular connectors for RS422 serial data transmission and reception.

- Power connector (2.1x5.5mm).
- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 200mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

Mounting methods

• Standard mounting is two D-rings, one at either end of the display.



• 1/4-20 nuts on the bottom of the unit for attaching feet or wall bracket. The feet or wall brackets are NOT included and may be ordered separately.

• The display has holes in the top for adding a handle. The handle is NOT included and may be ordered separately.

Features

- Two-digit count up timer settable to Day, Hour, Min or Sec.
- Two-digit count down timer settable to Day, Hour, Min or Sec.
- Count Up Timer with ground closure inputs or optional Start, Stop and Reset buttons.

• Digital Counter with ground closure inputs or optional Next (Increment), Previous (Decrement) and Reset buttons.

- Connect two or more TimeKeepers[™] together. One becomes the timer, and the others become remote displays.
- Two-digit count up timer settable to Day, Hour, Min or Sec.

• Two-digit count down timer settable to Day, Hour, Min or Sec.

Features with optional button module

- Count Up Timer.
- Count Down Timer. (0 to 99.59 MM:SS or 0 to 99:59:59 HH:MM:SS).
- User-programmable stored settings.
- Built-in time-of-day clock displays hours/minutes in 12/24 hour time or minutes/seconds.

In the Box

- DSP703B Large LED display
- RC Reference guide
- WD Wiring diagram
- M8BK003F Cable, 3ft, Cat-5
- Not Included: Keypad, transformer

