

# R2022A



## Features

- Two-Digit display for speeds from 0 to 199.
- RF wireless module permits the displays to be controlled remotely.
- Can be powered from DC power or from external 12V battery (see Options).

## In the Box

- R2022A Large LED display with 24" high digits.
- RC Reference guide
- WD Wiring diagram

## Required Accessories

- R2022A-KIT R2022A-25FT Power Cable, 15VDC 4A Power supply and AC power cord.

## Product

Wireless 24in 2.5-Digit RadarGun Readout

### Description:

2.5-Digit, 24" High display with Super Bright Red LEDs, Internal RF Wireless Transceiver, Integrated Gel Cell Battery and Charger, Handle and Feet, Water Resistant Enclosure, Metal Frame.

**Item:** R2022A

**UPC:** 788581657089

**EAN:** 0788581657089

**Stock Status:** Allow 3 weeks for delivery.

**Dimensions:** 36" x 30" x 3"

**Weight:** 20.5 lbs.

**MSRP:** \$4,099.00

## Specifications

- Two IP66 rated Conxall connectors for power and RS422 serial data transmission and reception.
- Test button for testing and configuration.
- Power requirements: 12-16VDC.
- Current consumption: 940mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.