

# RYG14AB-RF9



- Wireless.
- May be powered using AC or DC power.
- Low power consumption.

## In the Box

- RYG14AB-RF9 Indicator lamp module with wireless transceiver.
- RC Reference guide
- WD Wiring diagram
- Not Included: Transformer

## Product

Wireless Red-Yellow-Green Indicator

### Description:

Wireless table top Red-Yellow-Green Indicator unit, 1/2" diameter dome LEDs with beeper (Black ABS plastic enclosure).

**Item:** RYG14AB-RF9

**UPC:** 788581657553

**EAN:** 0788581657553

**Stock Status:** Usually in stock.

**Dimensions:** 5.63" x 3.25" x 1.5"

**Weight:** 0.5 lbs.

**MSRP:** \$369.00

## Specifications

- Wireless 900MHz transceiver.
- RJ45 modular connector for RS422 serial data input.
- RJ11 modular connectors for serial data input.
- Construction: ABS Plastic Enclosure, black.
- Power requirements: 10-13VAC or 12-15VDC.
- Current consumption: 100mA.

## Features

- Table Top Red-Yellow-Green Indicator.
- Red-Yellow-Green Audience signal lights.
- Works with The TimeKeeper™, Alzatex, Inc.'s zero to 99.59 minute Count Up/Down Timers.
- Built-in internal loud beeper. The Count Up/Down TimeKeeper™ can enable or disable the beeper.
- Green-Talk; Yellow-Wrap it up; Red-Done LED Indicators.