

SPE602S



- Test button for testing and configuration.
- Power requirements: 10-15VAC or 12-20VDC.
- Current consumption: 150mA maximum per digit.
- Construction: Metal enclosure, black powder coated finish with transparent red acrylic front.

Features

- Two-digit count up timer settable to Day, Hour, Min or Sec.
- Two-digit count down timer settable to Day, Hour, Min or Sec.

In the Box

- DSP602S Large LED display
- KP215ASM Remote keypad
- M8BK025F Cable, 25ft, Cat-5
- WTPS24W150 15VDC 1.6A Wall Adapter
- RC Reference guide
- WD Wiring diagram

Product

Digital LED Sports Display 6" Digits

Description:

Two-digit Race Clock with 6" high super bright red LED digits for sporting events, with handle, feet, water resistant enclosure, metal frame. Includes remote keypad, connection cable and power supply.

Item: SPE602S

UPC: 788581655177

EAN: 0788581655177

Stock Status: Usually in stock.

Dimensions: 13" x 10.5" x 2.5"

Weight: 24.4 lbs.

MSRP: \$1,134.00

Specifications

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- Power connector (2.1x5.5mm).