


TMR017B0-FM



Product

Remote 4-Digit Display

Description:

Remote Display with 4-digit seven segment Display with 0.56" high digits and Red-Yellow-Green warning LEDs, Black anodized AL, Flush-mount.

Item: TMR017B0-FM

UPC: 788581650141

EAN: 0788581650141

Stock Status: Usually in stock.

Dimensions: 4.6" x 3.25" x 1.5"

Weight: 0.4 lbs.

MSRP: \$299.00

Specifications

- One Serial data RJ11 connectors for accessories.
- Ground closure 600mA output for optional beeper. (not included).
- Construction: Metal flush mount plate, black powder coated finish.
- Power requirements: 10-18 VAC or 12-24 VDC power.
- Current consumption: 100ma.

Features

- Remote Display.

- User-programmable Green, Yellow and Red warning Indicators.
- Four-digit LED seven-segment Display with 0.56" high digits.
- Made of ruggedized aluminum construction.

In the Box

- TMR017B0-FM Flush mount LED display
- M4C007F 7ft Standard Modular phone cord
- RC Reference guide
- WD Wiring diagram
- Not Included: Transformer, controller

Required Accessories

- WT12VAC1200MA-RA 12V AC, 1200mA transformer

Stand alone, choose any Alzatex TimeKeeper™.

Examples:

- TMR223B5-SM Count up/down timer
- TMR223B8-SM Count up/down timer
- TMR223B8-FM Count up/down timer

Optional Accessories

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- DSP254B Large LED wall display
- DSP506B Large LED wall display
- DSP704B Large LED wall display
- KT6X422B Six Port RS422 Extender Driver module.
- RYG11ABBK Red-yellow-green indicator lamps

If you have a Crestron, AMX, RCI or PC, use the RS232 adapter

- PS1DB9B RS232 to RJ11 jack converter