## **TMR216B**





### **Product**

Up/Down Timer 6 Digits

#### **Description:**

Surface-mount Count Up/Down Timer with time-of-day clock, six-digit LED Display, 6 stored presets, and Red-Yellow-Green LEDs.

Item: TMR216B

UPC: 788581650271

EAN: 0788581650271

Stock Status: Usually in Stock.

**Dimensions:** 5.75" x 4" x 1.25"

Weight: 0.8 lbs. MSRP: \$595.00

## **Specifications**

- Two RJ45 modular connectors for RS422 serial data transmission and reception.
- Solder terminals for optional loud beeper.
- Construction: Metal enclosure, black powder coated finish
- Power requirements: 10-13VAC or 12-15VDC.

• Current consumption: 100mA.

#### **Features**

- Six-digit LED fourteen-segment alphanumeric Display with 0.54" high digits.
- Connect two or more TimeKeepers<sup>™</sup> together. One becomes the timer, and the others become remote displays.
- Six-digit count up timer settable to Day:Hour:Min, Hour:Min:Sec, or Min:Sec.Hundredths.
- Six-digit count down timer settable to Day:Hour:Min, Hour:Min:Sec.
- Made of ruggedized aluminum construction.
- Count Up Timer.
- Count Down Timer. (0 to 99.59 MM:SS or 0 to 99:59:59 HH:MM:SS).
- User-programmable Green, Yellow and Red warning Indicators.
- Internal beeper provides audible sound when the timer reaches zero.
- Button to turn beeper on/off.
- Up to 6 user-programmable stored settings.
- Built-in time-of-day clock displays hours/minutes in 12/24 hour time or minutes/seconds.
- Optional 900MHz or 2.4GHz RF Wireless communications interface.

#### In the Box

- TMR216B Count up/down timer
- RC Reference guide
- WD Wiring diagram
- CAT-5E cable, 7ft.
- Not Included: Transformer

## **Required Accessories**

WT12VAC1200MA-RA 12V AC, 1200mA transformer

# **Optional Accessories**

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- DSP254B Large LED wall display
- DSP506B Large LED wall display
- DSP704B Large LED wall display
- RYG11ABBK Red-yellow-green indicator lamps

If you have a Crestron, AMX, RCI or PC, use the RS232 adapter

PS422DB9A0 RS232 to RS422 converter.



