

# TMR223B3-FM



## Product

Flush Down Timer CLOCK 4-DIGIT Display

### Description:

Flush-mount Count Down Timer with time-of-day clock, 4-digit LED Display and Red-Yellow-Green LEDs.

**Item:** TMR223B3-FM

**UPC:** 788581650288

**EAN:** 0788581650288

**Stock Status:** Usually in stock.

**Dimensions:** 5.125" x 5.125" x 1.25"

**Weight:** 1 lbs.

**MSRP:** \$299.00

## Specifications

- Two RJ45 modular connectors for accessories.
- May be powered using 3-AA batteries or AC power.
- Ground closure 200mA output for optional beeper. (not included).

- Construction: Metal enclosure, black powder coated finish.
- Power requirements: 10-18 VAC or 12-24 VDC power.
- Current consumption: 100ma.

## Features

- Easy to use. Press Reset. Turn knob to set the desired time. Press Start.
- Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.
- Count Down time remaining Timer.
- 0-99.59 MM:SS or 0-99:59 HH:MM.
- User-programmable Green, Yellow and Red warning Indicators.
- The Select button selects between setting hours, minutes and seconds.
- Four-digit LED seven-segment Display with 0.56" high digits.
- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Four-digit count down timer settable to Min:Sec.
- Made of ruggedized aluminum construction.

## In the Box

- TMR223B3-FM Count down timer.
- RC Reference guide
- WD Wiring diagram
- M8BK007F 7ft, Cat-5, 8-conductor cable.
- Not Included: Transformer

## Required Accessories

- WT09VAC700MA-ST Wall transformer

## Optional Accessories

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- DSP254B Large LED wall display
- DSP506B Large LED wall display
- DSP704B Large LED wall display
- KT6X422B Six Port RS422 Extender Driver module.
- RYG11ABBK Red-yellow-green indicator lamps

If you have a Crestron, AMX, RCI or PC, use the RS232 adapter

- PS1DB9B RS232 to RJ11 jack converter