

TMR223B3-SM



Product

Count Down Timer CLOCK 4-DIGIT Display

Description:

Surface-mount Count Down Timer with time-of-day clock, 4-digit LED Display and Red-Yellow-Green LEDs.

Item: TMR223B3-SM

UPC: 788581650295

EAN: 0788581650295

Stock Status: Usually in stock.

Dimensions: 4.5" x 4.5" x 1.5"

Weight: 1 lbs.

MSRP: \$299.00

Specifications

- Two RJ45 modular connectors for accessories.
- May be powered using 3-AA batteries or AC power.
- Ground closure 200mA output for optional beeper. (not included).
- Construction: Metal enclosure, black powder coated finish.
- Power requirements: 10-18 VAC or 12-24 VDC power.

- Current consumption: 100ma.

Features

- Easy to use. Press Reset. Turn knob to set the desired time. Press Start.
- Subsequent timing cycles. Press Reset. The time previously used will be loaded. Press Start.
- Count Down time remaining Timer.
- 0-99.59 MM:SS or 0-99:59 HH:MM.
- User-programmable Green, Yellow and Red warning Indicators.
- The Select button selects between setting hours, minutes and seconds.
- Four-digit LED seven-segment Display with 0.56" high digits.
- Connect two or more TimeKeepers™ together. One becomes the timer, and the others become remote displays.
- Four-digit count up timer settable to Min:Sec.
- Made of ruggedized aluminum construction.

In the Box

- TMR223B3-SM Count down timer.
- RC Reference guide
- WD Wiring diagram
- M8BK007F 7ft, Cat-5, 8-conductor cable.
- Not Included: Transformer

Required Accessories

- WT12VAC1200MA-RA 12V AC, 1200mA transformer

Optional Accessories

Works with any size Alzatex display, Red-Yellow-Green indicator or TimeKeeper™. Examples:

- DSP254B Large LED wall display
- DSP506B Large LED wall display
- DSP704B Large LED wall display
- KT6X422B Six Port RS422 Extender Driver module.
- RYG11ABBK Red-yellow-green indicator lamps

If you have a Crestron, AMX, RCI or PC, use the RS232 adapter

- PS1DB9B RS232 to RJ11 jack converter